

Basic Specifications

| | |
|---------------|--|
| Model | ALSIR-2000 |
| Item number | 71112 |
| Description | Siren for wireless security system |
| Type | Security Plus-Line |
| Feature 1 | Will produce a loud sound (100 Decibel) when any of the connected sensors is triggered |
| Feature 2 | Can be placed at any indoor or outdoor location (IP44 water resistant) |
| Feature 3 | Long battery life and battery low indication to make sure the system always works |
| Code-system | Automatic |
| RF reach | Indoors up to 70 meters and outdoors 120 meters (depending on local conditions) |
| Compatibility | Works with all Trust Smart Home security Plus-Line products and ICS-2000 |
| Power supply | 4x Alkaline D type 1.5V batteries |
| Frequency | 868 MHz 2-way communication |

| | |
|----------------------------|----------------------|
| Blister material | PET |
| Products per package | 1x |
| Packages per inner carton | 7 |
| Packages per export carton | 14 |
| Weight per product | 543 g |
| Weight per packages | 799 g |
| Weight per inner carton | 6500 g |
| Weight per export carton | 12900g |
| Product size | 24,1 x 16,8 x 5,5 cm |
| Package size | 25,3 x 32,3 x 7,9 cm |
| Blister size | 25,6 x 32,6 x 8,2 cm |
| Inner carton size | 60 x 35.5 x 27.5cm |
| Export carton size | 61.5 x 36 x 57 cm |



ALSIR-2000

Advanced Specifications

| | |
|-------------------------------------|---|
| Tamper protection | Yes |
| Sound alarm (dB) | 100 dB +/- 5 dB |
| Duration of alarm | 4 min |
| Number of alarm tones | 3, 1 tone for alarming, 1 tone for sensor open warning and 1 tone for battery low |
| Mounting material included | Y, screws |
| Waterproof | Yes, IP44 water resistant |
| Max number linked devices | 16 |
| Activatie pairing mode | Hold learn button for about 1 sec |
| Pairing mode duration | 12 sec |
| Pairing mode indication | Red LED in cap will blink |
| Buttons and controls | Learn button, used for pairing and unpairing devices |
| Powered by | Battery 1,5V batteries |
| Running time battery | 18 months stand-by |
| Time to start sleepmodus | 3 sec |
| Wireless power | 10dBm max |
| Number of wireless connections ID's | 24 bit |

Unique Selling Points

- No payment of monthly fees required
- Easy to install; no need to call an electrician
- Anti-tamper system: the siren will be activated when the siren or one of the connected sensors is removed or opened
- The siren constantly checks the connected wireless sensors to make sure your home remains secure
- The wireless siren can be placed at any indoor or outdoor location (IP44 water resistant)
- You can add multiple sensors and/or remote controls



ALSIR-2000